

# ARTESYN ADQ600B SERIES

600 Watt Quarter Brick DC-DC Converter



ADQ600B series quarter-brick isolated DC-DC converters produce a single fully regulated 12 V output. Rated at 600 watts, these converters can deliver up to 50 amps output current and have no minimum load requirement. They have an input voltage range of 36 to 75 V and are primarily designed for use with standard 48 V supplies in computing and server applications, as well as regulated 48V supplies in communications equipment.

### **SPECIAL FEATURES**

- 600 W continuous power
- Ultra high efficiency: 95.5% typical at half load
- 36-75 Vdc Telecomm input range
- Baseplate optimized for contact
- cooling or heatsink mounting
- Trim -20% to +10% Vout
- Open frame version optimised for air cooling
- Low ripple and noise
- Fixed switching frequency
- High capacitive load capability
- Pre-bias start-up capability
- High reliability

- RoHS3.0 (2011/65/EU)
- UL94 V-0 materials
- DOSA footprint compliant
- PMBus Rev. 1.2 compliant
- Two year warranty (consult factory for extended terms)

#### SAFETY

- IEC/EN/UL/CSA 62368
- CE Mark
- UL/TUV
- UL94,V-0

## DATA SHEET

#### **Total Power:**

600 Watt (12V @ 50A)

#### **Input Voltage:**

36 - 75 V

#### # of Outputs:

Single (12 V Nom)







## **ELECTRICAL SPECIFICATIONS**

Input			
Input voltage	36 - 75 Vdc		
Input surge	100 V / 100 mSec		
Input UVLO	Turn-on: 35 Vdc Turn-off: 33 Vdc Hysteresis: 2 Vdc		
I/O insulation	Basic insulation		
I/O isolation	2250 Vdc		
Efficiency (48 Vin, 25 °C ambient)	94.5% @ 100% load (95.5% @ 50% load)		
Output			
Output voltage	12 V nominal set point		
Output voltage regulation	Line regulation: 20 mV typical Load regulation: 20 mV typical Temperature regulation: 0.002% / °C typical		
Output current maximum	50 A		
Noise/ripple	200 mVpp		
Overtemperature protection	120 °C hot spot		
Overvoltage protection Method / OVP operation	13.8 - 16 V window Auto restart / 130% Vout		
Overcurrent protection voltage Method / OCP operation	55 A -70 A window Hiccup at 140% lout		
Output voltage control	-20% to +10% Vout Trim		
Control			
Enable	TTL compatible (negative logic)		
Switching frequency	175 KHz		
Pre-bias start-up	0% to 95% Vout		

## ENVIRONMENTAL SPECIFICATIONS

Operating ambient temperature range	-40 °C to +85 °C
Storage temperature	-55 °C to +105 °C
Baseplate operating temperature	-40 °C to +100 °C (no power derating)
MTBF	1.5 Million hours





## MECHANICAL DRAWING - ADQ600B-48S12B-6LI







UNIT: mm[inch]

Note : There is no pin 9 -15 on ADQ600B-48S12B-6LK. UNIT: mm[inch]

TOLERANCE: X.X mm±0.5 mm[X.XX in. ±0.02 in.] X.XX mm±0.25 mm[X.XXX in. ±0.01 in.]



## ADQ600B

## **PIN ASSIGNMENTS**

Pin #	Name	Funtion	
1	+Vin	Positive input voltage	
2	Remote On/Off	Remote control	
3	-Vin	Negative input voltage	
4	-Vo	Negative output voltage	
5	-Sense	Remote sense negative	
6	Trim	Voltage adjustment	
7	+Sense Remote sense positi		
8	+Vo	Positive output voltage	
9	C2 Digital		
10	Sig_Gnd	Digital	
11	Data	Digital	
12	SMBAlert Digital		
13	Clock Digital		
14	Addr1	Digital	
15	Addr0 Digital		

Note - PIN9 - PIN 15; Only supported by ADQ600B-48S120-6LI.

Device code suffix	L		
-4	4.8 mm ± 0.5 mm		
-6	3.8 mm ± 0.5 mm		
-8	2.8 mm ± 0.25 mm		
None	5.8 mm ± 0.5 mm		

# ORDERING INFORMATION

Standard	Output Voltage	Structure	Remote ON/OFF logic	ROHS	Pmbus interface option
ADQ600B-48S12B-6LK	12 Vdc	Baseplate	Negative	RoHS3.0(2011/65/EU)	No.
ADQ600B-48S12B-6LI	12 Vdc	Baseplate	Negative	RoHS3.0(2011/65/EU)	Yes.

B = Baseplate I = PMBus interface version





Advanced Energy (AE) has devoted more than three decades to perfecting power for its global customers. AE designs and manufactures highly engineered, precision power conversion, measurement and control solutions for mission-critical applications and processes.

Our products enable customer innovation in complex applications for a wide range of industries including semiconductor equipment, industrial, manufacturing, telecommunications, data center computing, and medical. With deep applications know-how and responsive service and support across the globe, we build collaborative partnerships to meet rapid technological developments, propel growth for our customers, and innovate the future of power.

#### PRECISION | POWER | PERFORMANCE

Specifications are subject to change without notice. Not responsible for errors or omissions. ©2021 Advanced Energy Industries, Inc. All rights reserved. Advanced Energy®, AE® and Artesyn™ are U.S. trademarks of Advanced Energy Industries, Inc.



For international contact information, visit advancedenergy.com.

powersales@aei.com (Sales Support) productsupport.ep@aei.com (Technical Support) +1 888 412 7832